





| PERFORMANCE SPECIFICATION | MIN | TYP | MAX | UNITS |
|---|------|------|------|--------------------|
| Lower Frequency: | | | 150 | MHz |
| Upper Frequency: | 200 | | | MHz |
| Tuning Voltage: | 0.3 | | 4.7 | VDC |
| Supply Voltage: | 4.75 | 5.0 | 5.25 | VDC |
| Output Power: | 0 | +4.0 | +8.0 | dBm |
| Supply Current: | | | 35 | mA |
| Harmonic Suppression (2 nd Harmonic) | | -10 | | dBc |
| Pushing: | | | 1.0 | MHz/V |
| Pulling, all Phases: | | | 1.0 | MHz pk-pk |
| Tuning Sensitivity: | | 16 | | MHz/V |
| Phase Noise @ 10kHz offset: | | -115 | | dBc/Hz |
| Phase Noise @ 100kHz offset: | | -138 | | dBc/Hz |
| Load Impedance: | | 50 | | Ω |
| Input Capacitance: | | | 220 | pF |
| Operating Temperature Range: | -40 | | +85 | $^{\circ}\text{C}$ |
| Storage Temperature Range: | -45 | | +90 | $^{\circ}\text{C}$ |

FRONT



BACK



SIDE




● Unless otherwise specified, Dimensions are in: $\frac{\text{IN}}{(\text{mm})}$

Product Control:


| | | | |
|----------------------|--------------------|---------------|-------------|
| Crystek Part Number: | CRBV55CL-0150-0200 | Release Date: | 11-Sep-2019 |
| Revision Level: | D | Responsible: | C. Vales |



Phase Noise (1 Hz BW, Typical)



Tuning Curve (Typical)



Product Control:

| | | | |
|----------------------|--------------------|---------------|-------------|
| Crystek Part Number: | CRBV55CL-0150-0200 | Release Date: | 11-Sep-2019 |
| Revision Level: | D | Responsible: | C. Vales |

Crystek Corporation reserves the right to make changes to its products and/or information contained herein without notice. No liability is assumed as a result of its use or application.